

A whole home power solution during an outage. Safely connect a generator to your home in the case of an emergency without the worry of deadly back feeding of the utility lines. The EZ- Connect can support whole home generators so you won't miss a beat while the power is down.

Operating Range:

Utility: Up to 200 amps

Generator: 20 amps up to 200 amps at 240 volts

Switch Certification:

UL Listed disconnect switch

Enclosure Plug Options:

14-50 straight blade or hardwire

Generator Plug Options:

L14-20, L14-30, 14-50 straight blade, or hardwire

Enclosure:

NEMA 3R Rating

Size: 25 in. x16.5 in. x6in.

Models:

EZC: Base model

EZC-M-100/150/200: 100, 150A, Or 200A main disconnect (service rated)

EZC-R: 50A inlet for generator connection

EZC-MR-100/150/200: Main disconnect with inlet for generator connection

See price sheet for other options and descriptions

Options:

75kA surge protection

Cords to connect into a portable generator

Breaker (100, 150, or 200A) to become service entrance rated



Listed: E491124



Standard Features

- NEMA 3R enclosure
- UL Listed
- Double throw
- 240 VAC
- Up to 200 amps

Additional Products

- Dock Safe-Safety indicator
- Dock Out-Safety switch
- GenerLink-Transfer switch
- NE Meter-Sub meter
- Surge Safe-Surge protection

Lawrenceville, GA 30044

Phone: 800-886-3837 Fax: 888-886-3837

www.globalpowerproducts.com