



Philips Lighting Company

MATERIAL SAFETY DATA SHEET

PRODUCT: HIGH PRESSURE SODIUM LAMPS

Revised 8/02

SECTION 1: MANUFACTURER

Manufacturer's Name and Address: Philips Lighting Company
A Division of Philips Electronics
North America Corporation
200 Franklin Square Drive
Somerset, NJ 08875

Emergency Telephone No.: (800) 424-9300 CHEMTREC
(732) 563-3197

Other Information Calls: (607) 776-3311 Ext. 300

SECTION 2: HAZARDOUS INGREDIENTS

| | OSHA (PEL) mg/m ³ | ACGIH (TLV) mg/m ³ | % by Wt. |
|--------------------|---------------------------------|----------------------------------|---------------|
| Sodium (7440-23-5) | 2.0 8-TWA | Ceiling | less than .01 |
| Mercury (743-97-6) | .1 Ceiling | .025 8 hr. TWA | Less than .02 |
| Lead (7439-92-1) | .05 | | |

SECTION 3: PHYSICAL DATA

This item is a glass light bulb; chemical characteristics are not applicable.

SECTION 4: FIRE AND EXPLOSION DATA

Fire and explosion data not applicable. Under extreme heat outer glass envelope might melt or crack. Inner arc tube is composed of polycrystalline alumina and is refractory material.

SECTION 5: REACTIVITY DATA

Stability: Lamp is stable.

Incompatibility: Glass envelope will react with hydrofluoric acid.

Polymerization: Not applicable

SECTION 6: HEALTH HAZARD DATA

Not applicable to intact lamp. The inner envelope is composed of polycrystalline alumina. Breakage of this envelope may result in some exposure to elemental sodium and mercury. No adverse effects are expected from occasional exposure to broken lamps. As a matter of good practice, breakage should be avoided. Prolonged or frequent exposure to broken envelopes should be avoided through use of adequate ventilation during disposal of large quantities of lamps.

EMERGENCY AND FIRST AID PROCEDURE: Normal first aid procedure for glass cuts if such occur through lamp breakage.

SECTION 7: PRECAUTIONS FOR SAFE HANDLING AND USE

Normal precautions should be taken for collection of broken glass.

Waste Disposal Method: At the end of rated life, when this lamp is removed from service, it will be subjected to the current Toxic Characteristic Leaching Procedure (TCLP) prescribed by the Environmental Protection Agency. This test is used to determining whether an item is a hazardous waste or a non-hazardous waste under current E. P. A. definition. These lamps would fail the TCLP test and would be considered hazardous under the Universal Waste Rules. Generators should evaluate all of the disposal options, which may be available in the particular state in which the generator's facility is located. The generator should check with federal, state and local officials for their guidance. Philips encourages recycling of its products by qualified recyclers

SECTION 8: CONTROL MEASURES

Respiratory Protection: None. NIOSH-approved respirator might be used if large volumes of lamps are being broken for disposal.

Ventilation: Avoid inhalation of any airborne dust.

Hand and Eye Protection should be worn when handling broken glass.

SECTION 9: REGULATORY INFORMATION

As a product these mercury containing lamps being shipped in the manufacturer's original packaging are not regulated by air, truck or ocean shipment. As a waste, these spent fluorescent lamps would be regulated in various states and local communities. This material safety data sheet does not constitute "knowledge of the waste", in certain jurisdictions.

PHILIPS