

## SAVANT Sensor Switch

Single-Pole & 3-Way

1000W/VA

Incandescent, Magnetic Low-Voltage, Electronic Low-Voltage, Fluorescent, Compact Fluorescent, LED, Halogen



OS310U-W

### Features



- Can be wired as a Single-Pole or 3-Way device
- Selectable ON/OFF LED nightlight with press and hold dimming function
- Works with all popular load types: Incandescent, Magnetic Low-Voltage, Electronic Low-Voltage, Fluorescent, CFL and LED
- Green LED indicates load status, provides locator light in dark and blinks to indicate motion detection
- Push pad design provides minimal travel and crisp actuation
- Selectable time delay of 5 seconds (test), 5 minutes, 15 minutes and 30 minutes for lights to remain on after room is vacated
- Occupancy Sensors time delay default set to 5 minutes; Vacancy Sensors time delay default set to 30 minutes
- Occupancy Sensor provides a selectable ambient light override preventing lights from switching ON when there is acceptable natural light
- Occupancy Sensor Version allows to toggle between Auto-on/Auto-off or Manual ON/Auto-off mode with a simple press and hold of switch
- Uniform color matched PIR lens to device housing
- Replaces a standard light or fan switch
- Provides 180 degree field of view and 1000 sq. ft. of major motion coverage
- Provides true 3-Way operation when used with a 3-Way switch or sensor
- Occupancy Sensor provides for a bypass feature to allow the sensor to perform as a traditional switch (Manual ON/Manual OFF)
- Vacancy Sensor meets California 2008 Title 24
- Walk-in-Delay feature allows sensor to turn lights off without time delay when motion is detected briefly in room
- Electrostatic discharge protection
- No leakage to load in off mode
- Color change faceplate kits provide for a simple in field change
- Mid-Size Decorator wallplate included with product
- Neutral required for installation of device


#### Available Color Options

	Almond
	Black
	Gray
	Ivory
	Light Almond
	White

#### Load Types

	Incandescent/Halogen
	Fluorescent
	CFL
	Magnetic Low-Voltage
	Electronic Low-Voltage
	LED

#### Wiring Types



Single-Pole and 3-Way

**Reduce energy use and cut utility costs**

SAVANT sensors are ideal for any application with universal load and wiring compatibility, selectable and dimmable nightlight and unparalleled mode features.



**SAVANT Occupancy/Vacancy Sensor Switch**



Wattage	Lamp Type	Description	Cat. No.	Color
1000W/VA	Incandescent, MLV, ELV Fluorescent, CFL, LED, Halogen	Occupancy Sensor Switch with Nightlight and LED, Single-Pole/3-Way	<input type="checkbox"/> <b>OS310U-</b> __	A, BK, GY, LA, V, W
1000W/VA	Incandescent, MLV, ELV Fluorescent, CFL, LED, Halogen	Vacancy Sensor Switch with Nightlight and LED, Single-Pole/3-Way	<input type="checkbox"/> <b>VS310U-</b> __	A, BK, GY, LA, V, W
—	—	Color Change Kit	<input type="checkbox"/> <b>SCK1-</b> __-BP	A, BK, GY, LA, V, W

To indicate color when ordering, add one of the following suffixes to the Catalog Number: A (Almond), BK (Black), GY (Gray), LA (Light Almond), V (Ivory), W (White)  
 Note: All SAVANT sensors are rated for 120V/AC unless otherwise noted. Each device includes decorator mid-size wallplate.  
 For more information see specification information on page 51.  
 Derating information shown on page 47.

**Accessory Products**



*OS310R-LA  
SAVANT Sensor*



*OS106D1-LA  
SAVANT Sensor*



*AIM10-LA  
ACCELL Dimmer*



*DI06P-LA  
DEVINE Dimmer*



*PJS26LA  
Screwless Wallplate*