

Choose this generator for portable back-up during power outage or for power tools or RV's and trailers.

FUEL OPTION: *Powered By* **GASOLINE OR LPG FUEL**

DUAL FUEL



Flexible design lets you choose between **gasoline** or **liquid propane fuel**. The 120V RV outlet allows you to hook up to RV or trailer when camping or traveling.



9 HRS
@ 50% LOAD (GAS)
5 HRS
@ 50% LOAD (LP)
20 LB TANK

RUN TIME

6.2
GALLON
CAPACITY

FUEL TANK

389cc
OHV
4 STROKE
AIR COOLED

ENGINE

PROPANE FUEL HOSE WITH REGULATOR

INCLUDED

LIFETIME TECH SUPPORT
1 YEAR LIMITED WARRANTY
2 YEAR LIMITED EMISSION WARRANTY

WARRANTY

13
HORSE
POWER

HORSEPOWER

CONTROL PANEL FEATURES :



1 x 12 Volt D/C Outlet 2 x 120/240V Twist Lock 3 x 120 V RV Outlet 4 x 120 V GFCI A/C Outlet

This generator provides 6000 Running Watts (with 7500 Surge Watts)

Consider These Benefits When Using Propane Compared To Gasoline

- **Low Maintenance**
Propane generators have no carburetors, no gummed up fuel systems or stale gas.
 - **Environmentally Friendly**
Propane burns cleaner than natural gas.
 - **Infinite Fuel Shelf Life**
Propane will not degrade, so you can keep several propane tanks on hand and store them for an unlimited amount of time.
 - **Safety**
Gasoline spills contaminate and leave stains and odors; propane will dissipate into the air.
- Gas can and propane tank not included.



Wattage Consumption Guide

- 1 Using the item chart provided, select the items you wish to power at the same time. Then insert the corresponding numbers into the Running (Rated) Watts and Surge (Starting) Watts columns below.
- 2 Add up the Running (Rated) Watts of the items you wish to power and enter this number in the Total Running (Rated) Watts space.
- 3 Select the one individual item with the highest number of additional Surge (Starting) Watts. Take this one number, and add it to your Total Running (Rated) Watts, then enter it in the Total Surge (Starting) Watts space.

Tool or Appliance	Running (Rated) Watts	Surge (Starting) Watts
1. Refrigerator/Freezer	700	2200
2. 1/2 HP Furnace Fan	800	2350
3. Television	500	0
4. Lights (8 x 75 watts)	575	0
5. Microwave	625	0

Highest Additional Surge Watts

YOUR POWER NEEDS	Running (Rated) Watts	Surge (Starting) Watts
1.		
2.		
3.		
4.		
5.		

Total Running (Rated) Watts = 3200 **2350**
 Total Running (Rated) Watts = + 3200
 Total Surge (Starting) Watts = **5550**

Total Running (Rated) Watts = =
 Total Running (Rated) Watts = = +
 Total Surge (Starting) Watts = =

With this example you need a generator that produces at least 3200 total running watts and 5550 total starting watts.

The information above is estimates only. For best results, check your tool or appliance for exact wattage requirements. The wattages listed are based on wattage requirements. For exact wattages, check the data plate or owner's manual on the item you wish to power.

* SURGE WATTS / RUNNING WATTS MAY BE REDUCED BY 10% WHEN USING PROPANE FUEL VS USING GASOLINE.