

SPEAKER WIRE

APPLICATIONS Suitable for use as follows:

- Southwire's Speaker Wire is for use as a signal wire connecting amplifier and speakers in an audio system

CONSTRUCTION

- Southwire Speaker Wire is manufactured using stranded bare or tinned copper conductors laid parallel or round with an overall PVC insulation or CPE compound jacket with EPDM inliners.

WEIGHTS, MEASUREMENTS AND PACKAGING

| SIZE AWG | NO. OF COND. | CONDUCTOR STRAND | INSULATION THICKNESS | | NOMINAL OVERALL DIAMETER | | NET WEIGHT | |
|----------|--------------|------------------|----------------------|--------|--------------------------|-------------|------------|---------|
| | | | mm | inches | mm | inches | kg/km | lbs/Mft |
| 18 | 2 | 41 | 0 | 0 | 7.1 X 3.4 | .28 X .133 | 38.8 | 26.08 |
| 16 | 2 | 26 | .76 | .03 | 8.1 | .32 | 88.23 | 59.29 |
| 16 | 2 | 65 | 0 | 0 | 7.4 X 3.5 | .293 X .138 | 48.29 | 32.46 |
| 14 | 2 | 41 | 1.08 | .043 | 8.8 | .345 | 100.33 | 67.43 |
| 14 | 4 | 41 | 1.54 | .061 | 11 | .435 | 188.04 | 126.37 |



BLASTING CABLE/SPEAKER WIRE

Bare or Tinned Stranded Copper

Parallel Clear or Opaque PVC Insulation or EPDM Inliners

Two Copper Conductors

60°C/105°C