

Manual Start PORTABLE INVERTER GENERATOR

POWERING YOUR life.

#> Model 100306

UPC 817198020426

∑★ Warranty 3 Years



1600 RUNNING WATTS



Noise Level 53 dBA



EZ START DIAL Confusion free ENGINE START-UP



DIGITAL LED DISPLAY

Output, run time, fuel life and level



CLEAN ELECTRICITY

Power **SENSITIVE ELECTRONICS**



COLD START

Easy starts in **COLD WEATHER**



PARALLEL READY

Link 2 units for **DOUBLE POWER**PARA FINK

Receptacles



12V DC Automotive



20 AMP 120V, 5-20R

Q Specifications

START TYPE	Recoil
VOLTAGE (V)	120
ENGINE SIZE (cc)	80
FUEL TYPE	Gasoline
GASOLINE CAPACITY (gal.)	1.1
OIL TYPE	10W-30
OIL CAPACITY (qt.)	0.4
LOW OIL SHUT-OFF	Yes
EMISSIONS	EPA









Lightweight power and clever design are yours with the Champion 2000-watt stackable inverter generator. Rely on the 80cc engine and enjoy a quiet 53 dBA for up to 11 hours of run time. The optional ParaLINK Parallel Kit with RV Ready outlet and 30 amps of power doubles your output and saves space.

■ Inside the box

GENERATOR 12V USB ADAPTER

OPERATOR'S MANUAL
OIL FUNNEL

GASOLINE

ENGINE OIL (10W-30)

What You Need

(!) *Specifications, descriptions and illustrations are subject to change without notice.



