



POWERING YOUR *life.*

Model 100592

UPC 817198021928

Warranty 3 Years

7850
STARTING WATTS
Propane: 7050

6250
RUNNING WATTS
Propane: 5600

RUN TIME 10 hrs.

NOISE LEVEL 74 dBA



INTELLI GAUGE
3-MODE digital meter



VOLT GUARD
Protects against **POWER SURGES**



COLD START
Easy starts in **COLD WEATHER**

Receptacles



30 AMP
120/240V, L14-30R



20 AMP GFCI
120V, 5-20R



20 AMP GFCI
120V, 5-20R

Specifications

| | |
|------------------------------|---------------------|
| START TYPE | Recoil |
| VOLTAGE (V) | 120/240 |
| VOLTMETER | Intelligauge |
| ENGINE SIZE (cc) | 389 |
| FUEL TYPE | Gasoline or Propane |
| GASOLINE CAPACITY (gal.) | 6 |
| OIL TYPE | 10W-30 |
| OIL CAPACITY (fl. oz. / qt.) | 37.2 / 1.2 |
| LOW OIL SHUT-OFF | Yes |
| EMISSIONS | EPA/CARB |

*Specifications, descriptions and illustrations are subject to change without notice.

PACKAGE (gross)
Weight: 179 lb.
Size: 30.7 × 22.6 × 23.2 in.

PRODUCT (net)
Weight: 167 lb.
Size: 27 × 27.8 × 25 in.



CARBON MONOXIDE AUTO-SHUT OFF SYSTEM



GOT OIL?
10W-30
Oil not included
Aceite no incluido



Versatile power with peace of mind is yours with the Champion 6250-watt portable generator, which meets ANSI/PGMA G300-2018 requirements and features CO Shield™ - the Carbon Monoxide auto shutoff system. Dual Fuel technology allows the 389cc engine to safely operate on either gasoline or propane.

Inside the box

GENERATOR
WHEEL KIT
PROPANE HOSE 3.3 FT.

OIL FUNNEL
OPERATOR'S MANUAL

What You Need

GASOLINE
ENGINE OIL (10W-30)

WRENCH/SOCKET SET
PLIERS