

96801 - GE LED 4-Pin Vertical Plug-in

LED12G24Q-V/827

- GE's LED plug-in lamps allow you to replace inefficient CFL 4 pin G24q/GX24 without tools or costly upgrades. Simply plug the replacement lamp into the existing ballast.
- Uses 50% less energy than CFL (12W LED vs. 26W CFL)
- These lamps are energy efficient, contain no lead or mercury, and meet the material restriction requirements of RoHS
- For example, using only 12 watts of energy, save over \$71 in energy costs over the rated life of a lamp versus a standard 26-watt CFL lamp based on \$0.11 per kWh
- Advanced optics eliminate wasted light to deliver a more targeted beam with fewer lumens (950 vs. 1800)
- Energy efficiency and long life mean fewer lamp replacements versus CFL light sources
- Check ballast compatability at GELighting.com/LED4pincompatability

Product Photo



GENERAL CHARACTERISTICS

Base Description G24Q/GX24
Base Type 4-Pin Plug-in
Primary Application Indoor Damp
Product Color White
Product Technology LED
Rated Life (Hours) 50000 h

PHOTOMETRIC CHARACTERISTICS

Nominal Initial Lumen per Watt 79.2
Initial Lumens-nominal 950 lm
Color Rendering Index-CRI 80
Color Temperature 2700 K

PRODUCT INFORMATION

Product Code 96801

Description LED12G24Q-V/827

Alternative Unit Of Measure CASE

Standard Package Quantity

Ean UPC 043168968010 Standard Package GTIN 0043168968017

No Of Items Per Sales Unit No Of Items Per Standard Package

Sales Unit Case

UCC 043168968010

Alternative Unit Of Measure EACH
Standard Package Quantity 6

Ean UPC 043168968010 Standard Package GTIN 00043168968010

No Of Items Per Sales Unit 1
No Of Items Per Standard Package 6
Sales Unit Each

UCC 043168968010

DIMENSIONS

Bulb Max Overall Length-MOL 5.31 in

ELECTRICAL CHARACTERISTICS

Rated power (Watts) 12 W

CAUTIONS & WARNINGS

Caution

Risk of Electric Shock

Suitable for damp locations

Direct replacement for 13W/6T4/Q/G24q-1, 18W/7T4/Q/G24q-2, 26W/8T4/Q/G24q-3, 13W/5T4/M/GX24q-1, 18W/5T4/M/GX24q-2, 26W/8T4/Q/G24q-3, 18W/5T4/M/GX24q-3, 18W/5T4/

26W/6T4/M/GX24q-3 CFL lamps only

Not for use with dimmers

Not for use in totally enclosed recessed luminaires

For use only with compatible ballasts. See list at: www.gelighting/LED4pin-compatibility

Not intended for use with emergency exit lights

Do not use where directly exposed to water