

USE AND CARE GUIDE

OUTDOOR PENDANT



Questions, problems, missing parts? Before returning to the store, call Home Decorators Collection Customer Service.

8 a.m. - 7 p.m., EST, Monday-Friday, 9 a.m. - 6 p.m., EST, Saturday

1-800-986-3460

HOMEDEPOT.COM/HOMEDECORATORS

THANK YOU

Table of Contents

Table of Contents	2
Safety Information	
Warranty	
Pre-Installation	
Planning Installation	3
Tools Required	

Hardware Included	3
Package Contents	4
Installation	5
Operation	7
Care and Cleaning	7
Troubleshooting	7

Safety Information

 $\hfill \Box$



CAUTION: Inspect the wire insulation for any cuts, abrasions, or exposed copper that may have resulted during shipping. If there is a defect in the wire, do not attempt installation. Please call our Customer Service Team at 1-800-986-3460.



WARNING: Before starting installation of this fixture or removal of a previous fixture, disconnect the power by turning off the circuit breaker or by removing the fuse at the fuse box.

Warranty

The manufacturer warrants this lighting fixture to be free from defects in materials and workmanship for a period of three (3) years from date of purchase. This warranty applies only to the original consumer purchaser and only to products used in normal use and service. If this product is found to be defective, the manufacturer's only obligation, and your exclusive remedy, is the repair or replacement of the product at the manufacturer's discretion, provided that the product has not been damaged through misuse, abuse, accident, modifications, alterations, neglect, or mishandling. This warranty shall not apply to any product that is found to have been improperly installed, set-up, or used in any way not in accordance with the instructions supplied with the product. This warranty shall not apply to a failure of the product as a result of an accident, misuse, abuse, negligence, alteration, faulty installation, or any other failure not relating to faulty material or workmanship. This warranty shall not apply to the finish on any portion of the product, such as surface and/or weathering, as this is considered normal wear and tear. The manufacturer does not warrant and specifically disclaims any warranty, whether express or implied, of fitness for a particular purpose, other than the warranty contained herein. The manufacturer specifically disclaims any liability and shall not be liable for any consequential or incidental loss or damage, including but not limited to any labor / expense costs involved in the replacement or repair of said product.


Contact the Customer Service Team at 1-800-986-3460 or visit www.homedepot.com/homedecorators.

Pre-Installation


PLANNING INSTALLATION


- ☐ Read all instructions before installation.
- ☐ To avoid damaging this product, assemble it on a soft, non-abrasive surface, such as carpet or cardboard.
- \square Keep your receipt and these instructions for proof of purchase.

TOOLS REQUIRED



HARDWARE INCLUDED







Part	Description	Quantity
AA	Mounting unit	1
BB	Mounting screw	2
CC	Wire nut	3

Pre-Installation (continued)

PACKAGE CONTENTS








Part	Description	Quantity
Α	Light fixture	1
В	Canopy	1
С	Chain	1

Installation


1 Assembling the light fixture


□ Use a pair of pliers and a screwdriver (not included) to open the end links of the chain (C). Use a cloth on the pliers to protect the finish. Secure the chain (C) to the light fixture (A) by looping it through the ring. Use the pliers and a screwdriver to close the end link of the chain.




2 Attaching the mounting unit and canopy to the junction box

- Attach the mounting unit (AA) to the junction box (not included) with the mounting screws (BB) and remove the pre-installed screw collar ring.
- Place the canopy (B) over the pre-installed screw collar loop on the mounting unit (AA). Screw on previously removed screw collar ring until 1/2 of the screw collar loop threads are exposed.
- ☐ Use a pair of pliers and a screwdriver (not included) to open the end link of the chain (C) (opposite the light fixture). Use a cloth on the pliers to protect the finish. Secure the chain (C) to the screw collar loop on the mounting unit (AA). Use the pliers and a screwdriver to close the end link of the chain.
- Unscrew the screw collar ring and lower the canopy (B) over the chain (C). Weave the electrical wires, ground wires, and safety cable through the chain (C), screw collar loop, canopy (B) and through the center of the mounting unit (AA).









3 Making the electrical connection

- Connect the copper wire from the light fixture (A) to the mounting unit (AA) by securing it with the pre-installed ground screw.
- □ Connect the black to black (power), the white to white (neutral), and copper wire to ground wire with the wire nuts (CC) and secure the wire nuts (CC) with electrical tape (not included).







NOTE: If the wires from the fixture are the same color, attach the side with markings or letters to the black (positive) wire and the other to the white (neutral) wire.


Installation (continued)

4 Securing the light fixture

□ Place the canopy (B) over the pre-installed screw collar loop on the mounting unit (AA). Screw on the screw collar ring.




CAUTION: To avoid any waterproofing problems, please make sure the canopy fits the mounting surface perfectly during installation and use waterproof glue around the canopy for better sealing after installation.



5 Installing the light bulb

☐ Install one 60-watt max. medium-base bulb (not included).



Operation

1 Turning the light on

 $\hfill\Box$ Turn the light switch on to activate the fixture.

Care and Cleaning

- ☐ Clean the lamp with a soft, dry cloth.
- $\hfill\Box$

Troubleshooting

Problem	Possible Cause	Solution
The bulb will not light.	The power is off.	Ensure the power supply is On.
	There is a faulty wire connection.	Check the wiring.
	The circuit breaker is off.	Ensure the circuit breaker is in the On position.
The fuse blows or circuit breaker trips when the light is turned on.	There are crossed wires or the power wire is grounding out.	Check the wire connections. Contact a qualified electrician or call the Customer Service Team at 1-800-986-3460.



Questions, problems, missing parts? Before returning to the store, call Home Decorators Collection Customer Service.

8 a.m. - 7 p.m., EST, Monday-Friday, 9 a.m. - 6 p.m., EST, Saturday

1-800-986-3460

HOMEDEPOT.COM/HOMEDECORATORS

Retain this manual for future use.