Toggled LED Tubes - Dimmer Compatibility Listing

Toggled (dimmable) LED tubes perform best with ELV (reverse phase) type dimmers. ELV-type dimmers require a neutral wire at the switch and can be slightly more expensive, but typically resolve potential compatibility issues (including noise and/or flickering when dimming).

| | | | | | Tubes Pe | er Dimmer | |
|--------------|----------------|--------------|------------|--------|----------|-----------|--|
| | | Neutral Wire | 3-Way | Smart | | | |
| Manufacturer | Part Number | Required | Compatible | Dimmer | Min | Max | Comments |
| Lutron | SELV-300P | Х | | | 1 | 18 | Best performing, but requires neutral |
| Lutron | DVELV-300P | Х | | | 1 | 18 | Best performing, but requires neutral |
| Legrand | RHCL453PTCCCV6 | | Х | | 1 | 28 | Adjust low-end trim to minimum for deep dimming |
| Lutron | TGCL-153P | | Х | | 1 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | MACL-153M | | Х | | 1 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | PD-5NE | Х | | Х | 1 | 9 | Set to ELV mode for best performance |
| Lutron | CTCL-153P | | Х | | 2 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | SCL-153P | | Х | | 2 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | DVCL-153P | | Х | | 2 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | AYCL-253P | | Х | | 1 | 15 | Adjust low-end trim to minimum for deep dimming |
| Lutron | DVCL-253P | | Х | | 2 | 15 | Adjust low-end trim to minimum for deep dimming |
| Leviton | DSL06 | | Х | | 1 | 18 | Some flicker only when adjusting dimmer |
| Leviton | AWSMT-EB | Х | | | 1 | 30 | Wider than typical switches and narrow dimming range |

Toggled products: D416-30311, D416-40311, D416-50311, D416-65311

Toggled products: D416-30321, D416-40321, D416-50321, D416-65321

| | | | | Tubes Per Dimmer | | | |
|--------------|-------------|--------------------------|---------------------|------------------|-----|-----|--|
| Manufacturer | Part Number | Neutral Wire Required | 3-Way Compatible | Smart Dimmer | Min | Max | Comments |
| Lutron | SELV-300P | X | | | 1 | 18 | Best performing, but requires neutral |
| Lutron | DVELV-300P | Х | | | 1 | 18 | Best performing, but requires neutral |
| Lutron | TGCL-153P | | Х | | 1 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | PD-5NE | Х | | Х | 1 | 9 | Set to ELV mode for best performance |
| Lutron | CTCL-153P | | Х | | 2 | 9 | Adjust low-end trim to minimum for deep dimming |
| Lutron | SCL-153P | | Х | | 2 | 9 | Adjust low-end trim to minimum for deep dimming |
| Leviton | DSL06 | | Х | | 1 | 18 | Some flicker only when adjusting dimmer |
| Leviton | AWSMT-EB | Х | | | 1 | 30 | Wider than typical switches and narrow dimming range |

Toggled products: D312-XX321

| | | | | | Tubes Per Dimmer | | |
|--------------|-------------|--------------------------|---------------------|-----------------|------------------|-----|--|
| Manufacturer | Part Number | Neutral Wire Required | 3-Way Compatible | Smart Dimmer | Min | Max | Comments |
| Lutron | SELV-300P | X | compatible | Diminer | 1 | 25 | Best performing, but requires neutral |
| Lutron | DVELV-300P | Х | | | 1 | 25 | Best performing, but requires neutral |
| Lutron | TGCL-153P | | Х | | 1 | 12 | Adjust low-end trim to minimum for deep dimming |
| Lutron | PD-5NE | Х | | Х | 1 | 12 | Set to ELV mode for best performance |
| Lutron | CTCL-153P | | Х | | 1 | 12 | Adjust low-end trim to minimum for deep dimming |
| Lutron | SCL-153P | | Х | | 1 | 12 | Adjust low-end trim to minimum for deep dimming |
| Leviton | DSL06 | | Х | | 1 | 25 | Some flicker only when adjusting dimmer |
| Leviton | AWSMT-EB | Х | | | 1 | 41 | Wider than typical switches and narrow dimming range |

Toggled products: D208-XX321

| | | | | | Tubes Per Dimmer | | |
|--------------|-------------|--------------------------|---------------------|-----------------|------------------|-----|--|
| Manufacturer | Part Number | Neutral Wire Required | 3-Way Compatible | Smart Dimmer | Min | Max | Comments |
| Lutron | SELV-300P | X | - | | 1 | 37 | Best performing, but requires neutral |
| Lutron | DVELV-300P | Х | | | 1 | 37 | Best performing, but requires neutral |
| Lutron | TGCL-153P | | Х | | 1 | 18 | Adjust low-end trim to minimum for deep dimming |
| Lutron | PD-5NE | Х | | Х | 1 | 18 | Set to ELV mode for best performance |
| Lutron | CTCL-153P | | Х | | 1 | 18 | Adjust low-end trim to minimum for deep dimming |
| Lutron | SCL-153P | | Х | | 1 | 18 | Adjust low-end trim to minimum for deep dimming |
| Leviton | DSL06 | | Х | | 1 | 37 | Some flicker only when adjusting dimmer |
| Leviton | AWSMT-EB | Х | | | 1 | 62 | Wider than typical switches and narrow dimming range |